ADDITIONAL INFORMATION 04/01

At auxiliaries which are using DSI tomo with TDC (tomo density control) take care that the following settings are present to get a linear density voltage of 1 Volt:

<u>Program:</u>

- Registration devices
  - RGDV x
    - Data Set A:

Dose measurement input: EZX41
Dose measurement sensor type: . . . . Photo sensor/ampl. inp.

- Dose Rate Control
  - Amplimat
    - Chamber 5
      - **Data Set 1**
        <ESC>

Abbreviation:	[def1]	⎫
Dose Request Chamber [μGy/V]:	[6.40]	don't care the content
Dose of FSC [μGy]:	[2.14]	⎬ of these fields

kV70–Char. U_0 [kV]:	[40]		⎫
kV70–Char. Drel_0:	[**1.00**]	→	
kV70–Char. U_1 [kV]:	[40]		
kV70–Char. Drel_1:	[**1.00**]	→	
kV70–Char. U_2 [kV]:	[50]		
kV70–Char. Drel_2:	[**1.00**]	→	
kV70–Char. U_3 [kV]:	[60]		
kV70–Char. Drel_3:	[**1.00**]	→	
kV70–Char. U_4 [kV]:	[70]		**the fields of the kV**
kV70–Char. Drel_4:	[**1.00**]	→	**dependent correction**
kV70–Char. U_5 [kV]:	[80]		**factors must always**
kV70–Char. Drel_5:	[**1.00**]	→	**be at 1.00**
kV70–Char. U_6 [kV]:	[90]		
kV70–Char. Drel_6:	[**1.00**]	→	
kV70–Char. U_7 [kV]:	[110]		
kV70–Char. Drel_7:	[**1.00**]	→	
kV70–Char. U_8 [kV]:	[130]		
kV70–Char. Drel_8:	[**1.00**]	→	
kV70–Char. U_9 [kV]:	[150]		
kV70–Char. Drel_9:	[**1.00**]	→	⎭

RLF t_0 [ms]:	[0]	⎫
RLF Drel_0:	[1.000]	
RLF t_1 [ms]:	[20]	
RLF Drel_1:	[1.000]	
RLF t_2 [ms]:	[60]	
RLF Drel_2:	[1.000]	
RLF t_3 [ms]:	[100]	
RLF Drel_3:	[1.000]	
RLF t_4 [ms]:	[500]	
RLF Drel_4:	[1.000]	don't care the content
RLF t_5 [ms]:	[1000]	of the RLF fields
RLF Drel_5:	[1.000]	
RLF t_6 [ms]:	[1500]	
RLF Drel_6:	[1.000]	
RLF t_7 [ms]:	[2000]	
RLF Drel_7:	[1.000]	
RLF t_8 [ms]:	[3000]	
RLF Drel_8:	[1.000]	
RLF t_9 [ms]:	[4000]	
RLF Drel_9:	[1.000]	⎭